

# Order Guide 98-15-A1 B 1 4- B 0 B- N B

Series No.	(Table A)
Amp Rating.	(Table B)
Bushing Type.	(Table C)
Color of Button.	(Table D)
Terminal Type.	(Table E)
Voltage.	3=125/250Vdc, 4=125/250Vac, 32Vdc(Targa), 5=Client designation 9=CSA US type
Mounting Nut Type.	(Table F)
Waterproof Type.	(Table G)
Nameplate Type.	(Table H)
Terminal Finish.	N=Plate with Nickel O=No plate
Body Type.	B=Black W=White

(Table B) Bushing Type

Bushing Type= A1 Metal M11XP1.0	Bushing Type= B1 Metal M11XP1.0	Bushing Type= A2 Metal M12XP1.0	Bushing Type= A3 Metal 3/8"-27T
Bushing Type= B3 Metal 3/8"-27T	Bushing Type= B7 Metal 7/16"-17T	Bushing Type= P1 Plastic M11XP1.0	Bushing Type= P2 Plastic M12XP1.0
Bushing Type= P3 Plastic 3/8"-27T	Bushing Type= P5 Plastic Snap In	Bushing Type= KF Plastic Snap In	Bushing Type= HK Plastic Snap In
P1,A1,B1	A2,P2	P3,A3,B3	PS,KF,HK
Panel Hole			B7

(Table A) Standard Rating

03= 3.0A	15= 15.0A
3.5= 3.5A	16= 16.0A
04= 4.0A	17= 17.0A
05= 5.0A	18= 18.0A
06= 6.0A	20= 20.0A
07= 7.0A	22= 22.0A
08= 8.0A	25= 25.0A
09= 9.0A	30= 30.0A
10= 10.0A	35= 35.0A
11= 11.0A	40= 40.0A
12= 12.0A	45= 45.0A
13= 13.0A	50= 50.0A

(Table C) Color of Button Type

B	Black
W	White
R	Red
1	Black button w/ver White print
5	White button w/ver Black print
6	Red button w/ver White print

(Table D) Terminal Type

Type=1 Straight 11.6mm	Type=2 90° bend up	Type=3 90° bend down	Type=4 90° bend lead pin	Type=5 90° bend line pin	Type=6 Straight 8.0mm	Type=7 90° bend up/down	Type=8 45° bend up
Type=9 45° bend down	Type=X Straight 3.2mm	Type=F Screws #8-32	Type=L Screws #8-32	Type=J 90° bend down	Type=K Screws #8-32	Type=G Line pin 90° bend	Type=H Line pin 90° bend

(Table E) Mounting Nut Type

0	Type= P Plastic Integrated Kummut	Type= Q Plastic Kummut	Type= A Metal Kummut	Type= B Metal Hornut M11-H-14 M12-H-15	Type= C Metal	Type= 4 Plastic-Metal	Type= 5 Plastic-Metal	Type= 6 Plastic-Metal

(Table G) Nameplate Type

0	B	Black plate	A	Black plate	S	Black plate
None	W	White plate			X	White plate

(Table F) Waterproof Type

0	Type=R	Type=F	Type=V	Type=U
None				

- Table F Waterproof Type
- Table E Mounting Nut Type
- Table G Nameplate Type
- Table C Color of Button Type
- Table B Bushing Type
- Table D Terminal Type

